

Claims

What is claimed is:

- 1 1. An apparatus, including:
2 a modulator having a clock input including a duty cycle to be modulated by
3 an analog message signal, the modulator to provide a modulated carrier with a
4 monotonically-increasing fundamental frequency component to a switching
5 amplifier.

- 1 2. The apparatus of claim 1, wherein the duty cycle is limited to less than
2 about 50%.

- 1 3. The apparatus of claim 1, wherein the clock input includes a frequency
2 of about 500 MHz to about 100 GHz..

- 1 4. The apparatus of claim 1, wherein the clock input is used to initiate
2 charging and discharging of a capacitor.

- 1 5. The apparatus of claim 4, wherein a rate of discharge of the capacitor is
2 controlled by the analog message signal.

- 1 6. The apparatus of claim 1, wherein the analog message signal includes a
2 plurality of quadrature amplitude modulated symbols.

- 1 7. An apparatus, including:
2 a duty cycle modulator to raise and lower the mean value of a sinusoidal
3 signal according to a level of an analog message signal to provide a modulated

4 signal with a monotonically-increasing fundamental frequency component to a
5 switching amplifier.

1 8. The apparatus of claim 7, wherein the duty cycle is limited to less than
2 about 50%.

1 9. The apparatus of claim 7, wherein the analog message signal includes
2 quadrature amplitude modulated symbols.

1 10. A system, including:
2 a modulator having a clock input including a duty cycle to be modulated by
3 an analog message signal, the modulator to provide a modulated carrier with a
4 monotonically-increasing fundamental frequency component; and
5 a switching power amplifier to receive the modulated carrier and coupled to
6 the modulator.

1 11. The system of claim 10, further including:
2 a monopole antenna to couple to the switching power amplifier.

1 12. The system of claim 10, wherein the switching power amplifier is
2 selected from a class D amplifier, a class E amplifier, and a class S
3 amplifier.

1 13. The system of claim 10, further including:
2 a driver to directly couple the modulator to the switching power amplifier.

1 14. The system of claim 10, further including:
2 a digital-to-analog converter to provide the analog message signal.

1 15. A method, including:
2 adjusting a duty cycle of a switching amplifier input by changing an
3 amplitude of an analog message signal to provide a modulated carrier having a
4 monotonically-increasing fundamental frequency component.

1 16. The method of claim 15, wherein adjusting the duty cycle further
2 includes:
3 limiting the duty cycle to less than about 50%.

1 17. The method of claim 15, wherein the amplitude of the analog message
2 signal changes according to a multiple carrier communication technique.

1 18. The method of claim 17, wherein the multiple carrier communication
2 technique includes an orthogonal frequency division multiplexing
3 (OFDM) process.

1 19. The method of claim 15, further including:
2 pre-distorting a quadrature amplitude modulation (QAM) signal included in
3 the analog message signal to compensate non-linearity associated with the
4 switching amplifier.

1 20. The method of claim 15, further including:
2 pre-distorting an orthogonal frequency division multiplexed signal included
3 in the analog message signal to compensate non-linearity associated with the
4 switching amplifier.

1 21. An article comprising a machine-accessible medium having associated
2 information, wherein the information, when accessed, results in a
3 machine performing:

4 adjusting a duty cycle of a switching amplifier input by changing an
5 amplitude of an analog message signal to provide a modulated carrier having a
6 monotonically-increasing fundamental frequency component.

1 22. The article of claim 21, wherein adjusting the duty cycle further
2 includes:
3 limiting the duty cycle to less than about 50%.

1 23. The article of claim 21, wherein the analog message signal includes
2 quadrature amplitude modulated (QAM) symbols, and wherein the
3 information, when accessed, results in the machine performing:
4 pre-distorting a quadrature amplitude modulation (QAM) signal included in
5 the analog message signal to compensate non-linearity associated with the
6 switching amplifier.

1 24. The article of claim 24, wherein the analog message signal includes an
2 orthogonal frequency division multiplexed (OFDM) signal, and wherein
3 the information, when accessed, results in the machine performing:
4 pre-distorting the OFDM signal included in the analog message signal to
5 compensate non-linearity associated with the switching amplifier.